C-2389

<div align="center">

TITLE OF THE INVENTION

Procedure for Shutting Down a
Fuel Cell System Using Air Purge

</div>

5

<div align="center">

BACKGROUND OF THE INVENTION

</div>

TECHNICAL FIELD

This invention relates to fuel cell systems and,
more particularly, to procedures for shutting down an
10 operating fuel cell.

BACKGROUND INFORMATION

It is well known in the fuel cell art that, when the
electrical circuit is opened and there is no longer a
load across the cell, such as upon and during shut-down
15 of the cell, the presence of air on the cathode, coupled
with hydrogen fuel remaining on the anode, often cause
unacceptable anode and cathode potentials, resulting in
catalyst and catalyst support oxidation and corrosion and
attendant cell performance degradation. It was thought
20 that inert gas needed to be used to purge both the anode
flow field and the cathode flow field immediately upon
cell shut-down to passivate the anode and cathode so as
to minimize or prevent such cell performance degradation.
Further, the use of an inert gas purge avoided the
25 possible occurrence of a flammable mixture of hydrogen
and air, which is a safety issue. While the use of 100%
inert gas as the purge gas is most common in the prior
art, commonly owned U. S. Patents 5,013,617 and 5,045,414
describe using 100% nitrogen as the anode side purge gas,
30 and a cathode side purging mixture comprising a very
small percentage of oxygen (e.g. less than 1%) with a
balance of nitrogen. Both of these patents also discuss
the option of connecting a dummy electrical across the
cell during the start of purge to lower the cathode

potential rapidly to between the acceptable limits of
0.3-0.7 volt.

It is undesirable to use nitrogen or other inert gas
as a shut-down or start-up purge gas for fuel cells where
5 compactness and service interval of the fuel cell
powerplant is important, such as for automotive
applications. Additionally, it is desired to avoid the
costs associated with storing and delivering inert gas to
the cells. Therefore, safe, cost effective shut-down and
10 start-up procedures are needed that do not cause
significant performance degradation and do not require
the use of inert gases, or any other gases not otherwise
required for normal fuel cell operation.

15   BRIEF SUMMARY OF THE INVENTION
In accordance with the present invention, a
procedure for shutting down an operating fuel cell system
includes disconnecting the primary electricity using
device and stopping the flow of hydrogen containing fuel
20 to the anode, followed by displacing the fuel remaining
in the anode fuel flow field with air by blowing air
through the anode fuel flow field.

In one experiment using a stack of PEM fuel cells of
the general type described in commonly owned U. S. Patent
25 5,503,944, the primary electricity using device was
disconnected, and the flow of fuel (hydrogen) to the
anode and the flow of air to the cathode were shut off.
No attempt was made to purge the anode flow field of
residual fuel or to purge the cathode flow field of air,
30 such as by using an inert gas purge. To restart the
cell, fuel and oxidant were flowed directly into their
respective flow fields. (The foregoing procedure is
hereinafter referred to as an "uncontrolled" start/stop
cycle.) It was found that a cell stack assembly operated
35 in this manner experienced rapid performance decay which
had not previously been observed. (This is further

2

discussed hereinafter in connection with curve "J" of
Fig. 3.) Further, it was discovered that a large number
of start/stop cycles were more detrimental to cell
performance than were a large number of normal operating
5 hours under load. It was eventually determined, through
experimentation, that both the shut-down and start-up
procedures were contributing to the rapid performance
decay being experienced by the cell; and it was known
that such rapid decay did not occur when, in accordance
10 with prior art techniques, inert gas was used to
passivate the cell at each shut down. Examination of
used cells that experienced only a few dozen uncontrolled
start/stop cycles showed that 25% to 50% of the high
surface area carbon black cathode catalyst support was
15 corroded away, which had not previously been reported in
the prior art.

Further testing and analysis of results led to the
belief that the following mechanism caused the
performance decay experienced in the foregoing
20 experiment: With reference to Fig. 2, a diagrammatic
depiction of a PEM fuel cell is shown. (Note that the
mechanism to be described is also applicable to cells
using other electrolytes, such as phosphoric acid or
potassium hydroxide with appropriate changes in ion
25 fluxes.) In Fig. 2, M represents a proton exchange
membrane (PEM) having a cathode catalyst layer C on one
side and an anode catalyst layer A on the other side. The
cathode air flow field carrying air to the cathode
catalyst is divided into air zones 1 and 2 by a dotted
30 line. The anode fuel flow field that normally carries
hydrogen over the anode catalyst from an inlet I to an
exit E is also divided into two zones by the same dotted
line. The zone to the left of the dotted line and
adjacent the inlet I is filled with hydrogen and labeled
35 with the symbol H_2. The zone to the right of the dotted

3

line and adjacent the exit E is zone 3 and is filled with air.

Upon an uncontrolled shut-down (i.e. a shut-down without taking any special steps to limit performance decay) some of the residual hydrogen and some of the oxygen in their respective anode and cathode flow fields diffuse across the PEM (each to the opposite side of the cell) and react on the catalyst (with either oxygen or hydrogen, as the case may be) to form water. The consumption of hydrogen on the anode lowers the pressure in the anode flow field to below ambient pressure, resulting in external air being drawn into the anode flow field at exit E creating a hydrogen/air front (the dotted line in Fig. 2) that moves slowly through the anode flow field from the fuel exit E to the fuel inlet I. Eventually the anode flow field (and the cathode flow field) fills entirely with air. Upon start-up of the cell, a flow of air is directed into and through the cathode flow field and a flow of hydrogen is introduced into the anode flow field inlet I. On the anode side of the cell this results in the creation of a hydrogen/air front (which is also represented by the dotted line in Fig. 2) that moves across the anode through the anode flow field, displacing the air in front of it, which is pushed out of the cell. In either case, (i.e. upon shut-down and upon start-up) a hydrogen/air front moves through the cell. On one side of the moving front (in the zone H_2 in Fig. 2) the anode is exposed substantially only to fuel (i.e. hydrogen); and in zone 1 of the cathode flow field, opposite zone H_2, the cathode is exposed only to air. That region of the cell is hereinafter referred to as the H_2/air region: i.e. hydrogen on the anode and air on the cathode. On the other side of the moving front the anode is exposed essentially only to air; and zone 2 of the cathode flow field, opposite zone 3, is also exposed to air. That

4

region of the cell is hereinafter referred to as the
air/air region: i.e. air on both the anode and cathode.

The presence of both hydrogen and air within the
anode flow field results in a shorted cell between the
portion of the anode that sees hydrogen and the portion
of the anode that sees air. This results in small in-
plane flow of protons (H^+) within the membrane M and a
more significant through-plane flow of protons across the
membrane, in the direction of the arrows labeled H^+, as
well as an in-plane flow of electrons (e^-) on each side of
the cell, as depicted by the arrows so labeled. The
electrons travel through the conductive catalyst layers
and other conductive cell elements that may contact the
catalyst layer. On the anode side the electrons travel
from the portion of the anode that sees hydrogen to the
portion that sees air; and on the cathode side they
travel in the opposite direction.

The flow of electrons from the portion of the anode
that sees hydrogen to the portion of the anode that sees
air results in a small change in the potential of the
electron conductor. On the other hand, electrolytes in
the membrane are relatively poor in-plane proton
conductors, and the flow of protons results in a very
significant drop in the electrolyte potential between
zones H_2 and 3.

It is estimated that the reduction in electrolyte
potential between zones H_2 and 3 is on the order of the
typical cell open circuit voltage of about 0.9-1.0 volts.
This drop in potential results in a proton flow across
the PEM, M, from the cathode side, zone 2, to the anode
side, zone 3, which is the reverse direction from what
occurs under normal cell operating conditions. It is
also estimated that the reduction in electrolyte
potential in the portion of the anode that sees air (in
zone 3) results in a cathode potential in zone 2 of
approximately 1.5 to 1.8 volts, versus the normal cathode

potential of 0.9 to 1.0 volts. (Note: These potentials
are relative to the hydrogen potential at the same
operating conditions.) This elevated cathode potential
results in rapid corrosion of the carbon support material
5   and the cathode catalyst, causing significant cell
performance decay.

One object of the present invention is to minimize
any fuel cell catalyst and catalyst support corrosion
occurring during shut-down of the fuel cell, and to do it
10   without purging air from the cells with inert gas upon
shut-down.

In accordance with one embodiment of the present
invention, a shut-down procedure includes the steps of
disconnecting the primary load from the cell; halting the
15   flow of fuel to the anode and the flow of air to the
cathode; and then blowing air under pressure into and
through the anode flow field to rapidly displace all the
hydrogen remaining in the anode flow field. Displacing
the hydrogen quickly reduces the period of time that
20   platinum and carbon corrosion occurs, as compared with
simply allowing the air to be drawn slowly into the cell
as a result of falling hydrogen pressure over an extended
period of time, which may be as long as 30 to 60 seconds
or more. Although dependant upon the cell materials,
25   desired length of cell life, and the number of shut-downs
and start-ups likely to occur during that life, it is
believed the hydrogen/air front will need to move through
the anode in no more than about 1.0 second to satisfy
performance needs over the life of the cell without
30   requiring an inert gas purge. Preferably the purge air
flow rate will move the H_2/air front (and thus all the
hydrogen) through and out of the anode flow field in less
than 0.2 seconds. For long life applications, such as
automotive applications, with frequent start-ups and
35   shut-downs, a purge time of 0.05 seconds or less is most
preferable.

6

In a preferred embodiment of the invention, after the primary load is disconnected and the fuel and oxidant flow to the cell is stopped, a small auxiliary resistive load is connected across the cell for a period of time

5 immediately prior to blowing air through the anode flow field. The application of the auxiliary load prior to the purging step consumes hydrogen in the anode flow field through the occurrence of normal electrochemical reactions. Then, when the step of blowing air through

10 the anode flow field commences, the cathode potential will have been significantly lowered, and, consequently, the rate of catalyst and catalyst support corrosion during the air purge will be lower. Note that, in this embodiment, the auxiliary load may be disconnected prior

15 to commencing the air purge, or it may be continued during at least a portion of or throughout the air purge.

The following commonly owned U. S. non-provisional patent application, filed on even date with this patent application, describes and claims an invention related to

20 the subject matter of this application: USSN (Assignee Docket # C-2405) "Procedure for Starting Up a Fuel Cell System Using a Fuel Purge", invented by Carl Reiser, Richard Sawyer, and Deliang Yang.

The foregoing features and advantages of the present

25 invention will become more apparent in light of the following detailed description of exemplary embodiments thereof as illustrated in the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

30 Fig. 1 is a schematic depiction of a fuel cell system that may be operated in accordance with the shut-down procedures of the present invention.

Fig. 2 is a diagrammatic view of a fuel cell cross-section used to explain a mechanism that may cause cell

35 performance degradation during start-up and shut-down.

7

Fig. 3 is a graph showing the effect of the number of start-up/shut-down cycles on fuel cell performance using various start-up/shut-down procedures, including prior art procedures and the procedures of the present

5 invention.

DETAILED DESCRIPTION OF THE INVENTION

In Fig. 1, a fuel cell system 100 is shown. The system includes a fuel cell 102 comprising an anode 104,

10 a cathode 106, and an electrolyte layer 108 disposed between the anode and cathode. The anode includes an anode substrate 110 having an anode catalyst layer 112 disposed thereon on the side of the substrate facing the electrolyte layer 108. The cathode includes a cathode

15 substrate 114, having a cathode catalyst layer 116 disposed thereon on the side of the substrate facing the electrolyte layer 108. The cell also includes an anode flow field plate 118 adjacent the anode substrate 110, and a cathode flow field plate 120 adjacent the cathode

20 substrate 114.

The cathode flow field plate 120 has a plurality of channels 122 extending thereacross adjacent the cathode substrate forming a cathode flow field for carrying an oxidant, preferably air, across the cathode from an inlet

25 124 to an outlet 126. The anode flow field plate 118 has a plurality of channels 128 extending thereacross adjacent the anode substrate forming an anode flow field for carrying a hydrogen containing fuel across the anode from an inlet 130 to an outlet 132. Each cell also

30 includes a cooler 131 adjacent the cathode flow field plate 120 for removing heat from the cell, such as by using a water pump 134 to circulate water through a loop 132 that passes through the cooler 131, a radiator 136 for rejecting the heat, and a flow control valve or

35 orifice 138.

Although only a single cell 120 is shown, in actuality a fuel cell system would comprise a plurality of adjacent cells (i.e. a stack of cells) connected electrically in series, each having a cooler separating the cathode flow field plate of one cell from an anode flow field plate of the adjacent cell. For more detailed information regarding fuel cells like the one represented in Fig. 1, the reader is directed to commonly owned U.S. Patents 5,503,944 and 4,115,627, both of which are incorporated herein by reference. The '944 patent describes a solid polymer electrolyte fuel cell wherein the electrolyte layer is a proton exchange membrane (PEM). The '627 patent describes a phosphoric acid electrolyte fuel cell wherein the electrolyte is a liquid retained within a porous silicon carbide matrix layer.

Normal Operation

Referring, again, to Fig. 1, the fuel cell system includes a source 140 of fresh hydrogen containing fuel, under pressure, a source 142 of air, an air blower 144, a primary electricity using device or primary load 146, an auxiliary load 148, an anode exhaust recycle loop 150, and a recycle loop blower 152. (By "fresh" hydrogen containing fuel, it is meant fuel that has not yet been introduced into the fuel cell, as opposed to fuel that has been partially consumed within the cell and recirculated through the cell.) During normal fuel cell operation, when the cell is providing electricity to the primary load 146, a primary load switch 154 is closed (it is shown open in the drawing), and an auxiliary load switch 156 is open. The air blower 144, anode exhaust recycle blower 152 and coolant pump 134 are all on, and a valve 166 in a fuel feed conduit from the fuel source 140 into the anode recycle loop 150 downstream of the recycle blower 152 is open, as is the valve 170 in the recycle loop 150 and the anode exhaust vent valve 172 in an anode

9

exhaust conduit 174. An air inlet feed valve 158 in the
conduit 160 is open. An air feed valve 162 in a conduit
164 from the air source 142 to a point in the recycle
loop upstream of the recycle blower 152 is closed.

5   Thus, during normal operation, air from the source
142 is continuously delivered into the cathode flow field
inlet 124 via the conduit 160 and leaves the cell outlet
126 via a conduit 176. Fresh hydrogen containing fuel
from the pressurized source 140 is continuously delivered

10 into the anode flow field via the conduit 168, which
directs the fuel into the recycle loop 150. A portion of
the anode exhaust, containing depleted fuel leaves the
anode flow field through the vent valve 172 via the
conduit 174, while the recycle blower 152 recirculates

15 the balance of the anode exhaust through the anode flow
field via the recycle loop in a manner well know in the
prior art. The recycle flow helps maintain a relatively
uniform gas composition from the inlet 130 to the outlet
132 of the anode flow field, as well as returning some

20 water vapor to the cell to prevent dry-out of the cell in
the vicinity of the fuel inlet. The hydrogen in the fuel
electrochemically reacts in a well-known manner during
normal cell operation to produce protons (hydrogen ions)
and electrons. The electrons flow from the anode 104 to

25 the cathode 106 through an external circuit 178 to power
the load 146, while the protons flow from the anode 104
to the cathode 106 through the electrolyte 108.

Shut-down Procedure

30   In accordance with an exemplary embodiment of the
present invention, to avoid significant cell performance
decay as a result of corrosion of the cell catalyst and
catalyst support the following procedure may be used to
shut down the cell: The switch 154 is opened,

35 disconnecting the primary load from the external circuit.
The valve 166 is closed to stop the flow of fuel to the

10

anode flow field. The air inlet feed valve 158 is
preferably closed, as well as the anode vent valve. (The
valve 158 could be left open, allowing air flow through
the cathode, if desired.) The recycle flow valve 170 may

5 remain open and the recycle blower 152 may remain on in
order to continue to recirculate the anode exhaust
through the cell. This prevents localized fuel
starvation on the anode. The switch 156 is then closed,
thereby connecting the small auxiliary resistive load 148

10 across the cell in the external circuit 178. With the
switch 156 closed, the usual cell electrochemical
reactions continue to occur such that the hydrogen
concentration in the anode flow field is reduced.

The valve 162 (or other valve that may provide a

15 source of ambient air into the recycle loop 150, such as
the valve 180 in the conduit 182, shown in phantom for
use in connection with another embodiment hereinafter
described) may be partially opened during the period of
auxiliary load application to prevent the pressure in the

20 anode chamber from dropping below ambient pressure, and
to prevent random air leaks into the anode flow field.
The oxygen in the air also hastens the consumption of
hydrogen by reacting with the hydrogen on the anode
catalyst.

25 The auxiliary load 148 is preferably sized to lower
the cell voltage from its open circuit voltage of about
0.90-1.0 volts to about 0.20 volts in about 15 seconds to
one minute. The size of the load necessary to accomplish
this will depend upon the particulars of the cell design,

30 such as number of cells, size of cells, and the maximum
volume of hydrogen within the anode flow field and any
fuel manifolds or the like. Note that the first 0.10
volt drop in cell voltage (from, for example, an initial
voltage of 0.95 volts to a voltage of 0.85 volts) reduces

35 the amount of hydrogen on anode side by more than two
orders of magnitude (i.e. from 100% hydrogen to less than

11

1% hydrogen) for the case where the air valve 158 is open. Thus, even if the auxiliary load reduced the cell voltage by only 0.1 volt, this would be very beneficial to the shut-down process. During the period of low level
5 current production resulting from application of the auxiliary load prior to the commencement of the air purge, no hydrogen/air front traverses the cell; and, as a result of the application of the auxiliary load, the magnitude of the "reverse currents" believed to cause
10 cell performance decay during shut-down will be lower during the air purge step.

    Once the cell voltage has been reduced by a predetermined amount (preferably by at least 0.1 volts, and most preferably to a cell voltage of 0.2 volts or
15 less), the switch 156 may be opened, or it may remain closed during all or part of the remainder of the shut-down procedure. The recycle valve 170 is closed to prevent further recirculation of the anode exhaust. The anode exhaust vent valve is opened, and the air flow
20 valve 162 is then opened to allow air from the source 142 into the recycle loop immediately downstream of the valve 170 and just upstream of the recycle blower 152. The blower 152 blows this air directly into and through the channels 128 of the anode flow field, quickly displacing
25 any fuel remaining therein. That fuel, with the air behind it, leaves the cell through the vent valve 172. The anode flow field is now filled entirely with air, and the blower 152 may be shut off.

    Although in the foregoing embodiment an auxiliary
30 load is used to reduce cell voltage before commencing with the step of displacing the hydrogen with air, for some applications, if the speed of the air purge is sufficiently fast and/or the number of on/off cycles required during the life of the cell is sufficiently
35 small, unacceptable performance decay caused by shut-down procedures may be avoided without the step of applying an

12

auxiliary load. In such an application the air purge
would be initiated immediately upon disconnecting the
primary load.

     In the fuel cell system just described, the recycle
5 blower 152 is used to blow purge air through the anode
flow field to displace the hydrogen therein. If the fuel
cell system did not have a recycle loop 150, the air
blower 144 could perform the purging function of the
recycle blower 152 during the shut-down procedure by
10 connecting a conduit 180 (shown in phantom) from the
conduit 160 directly into the anode flow field inlet.
After the switch 156 and the vent valve 172 are opened,
the valve 182 in a conduit 180, is opened. The blower
144 then blows purge air from the source 142, through the
15 conduit 180, and directly into the fuel inlet 130 to
create a front of air (herein usually referred to as a
"hydrogen/air" front because hydrogen is on one side and
air is on the other) that sweeps through the anode flow
field. (Note that, as in other embodiments, the
20 auxiliary load 148 may still be connected across the cell
prior to purging to electrochemically consume a portion
of and preferably most of hydrogen residing in the anode
flow field.)

     In some fuel cell systems the anode and cathode flow
25 field plates and the cooler plate, such as the plates
118, 122 and 131, or the like are porous and used to both
carry gasses to the cell anode and cathode and to
transport water away from the cells. In those systems,
the coolant loop pump, such as the pump 134, should
30 remain on during the shut-down procedure of the present
invention. This prevents reactant channels from becoming
blocked by coolant draining from coolant channels.
Blocked reactant channels may make the shut-down
procedure of the present invention (as well as the
35 analogous start-up procedure described below) ineffective
by preventing reactant gasses from readily reaching

13

portions of the anode and cathode catalysts. Once the
cells are free of hydrogen, the coolant loop pump may be
turned off.

5 Start-up Procedure

    Assume, now, that the cell has been shut-down in
accordance with the procedure of the present invention
and has only air within the anode and cathode flow
fields. To restart the fuel cell system 100, the coolant
10 loop valve 138, if closed, is opened. The switch 156
remains open, as the auxiliary load is not used during
start-up. The air flow valve 158 is preferably open, but
it may be closed; and the blower 144 and pump 134 are
turned on. The anode exhaust vent valve 172 is open and
15 the air flow valve in the conduit 162 is closed. The
recycle flow valve 170 is also closed, and the recycle
blower is off. The fuel flow valve 166 is opened to
allow a flow of pressurized hydrogen from the source 140
into the anode flow field. The hydrogen flow pushes the
20 air out of the anode flow field. When substantially all
the air has been displaced from the anode flow field, the
switch 154 is closed to connect the primary load across
the cell 102. (If the air flow valve was closed, it is
opened prior to closing the switch 154.) The cell may
25 now be operated normally.

    During shut-down best results are achieved when fuel
in the anode flow field is displaced with air as quickly
as possible. Similarly, during start-up, it is preferred
to displace the air within the anode flow field with fuel
30 as quickly as possible. In either case the displacement
should occur in less than about 1.0 seconds, and
preferably less than 0.2 seconds. For long life
applications with a high number of start-stop cycles,
such as for automotive applications, it is most
35 preferable to purge the fuel from the anode flow field at
shut-down and to purge the air from the anode flow field

14

at start-up in less than 0.05 seconds. Blowers and other
devices used to move the gases through the system may
easily be selected to achieve the desired speed with
which the hydrogen/air front is to move through the cell
5 and thus purge the cell of undesired gases.

Compared to shutting down and starting up the fuel
cell system by simply turning the fuel supply off and on
with no purge or other performance decay limiting
intervention (i.e. uncontrolled start/stop), the rapid
10 air purge of fuel from the anode flow field at shut-down
and the rapid hydrogen purge of air from the anode flow
field upon start-up significantly increases cell life by
reducing cumulative cell performance losses resulting
from repeated shut-downs and start-ups. This is shown in
15 the graph of Fig. 3. In Fig. 3, the vertical axis is
average cell performance loss, in volts; and the
horizontal axis is the number of cell start-ups. The
curves J, K, and L represent data from the actual testing
of 20 or 56 cell PEM cell stacks. The cells in the stack
20 each included a membrane electrode assembly comprising a
15 micron thick perfluorosulfonic ionomer membrane having
a platinum catalyst on the anode side and a platinum
catalyst on the cathode side. The anode catalyst loading
was 0.1 mg/cm^2, and the cathode catalyst loading was 0.4
25 mg/ cm^2. The assembly was supplied by W. L. Gore Company
of Elkton, Maryland under the trade name PRIMEA 5560.

The curve J represents "uncontrolled" start-up and
shut-down cycles. Over the course of the 250 or so
cycles depicted by the curve, the start-up procedure was
30 to initiate hydrogen flow into the air filled anode flow
field at varying "uncontrolled" rates. A typical rate
was one that was sufficient to produce a full anode flow
field volume change in 10.0 seconds; however, the start-
up flow rate for some cycles was as fast as 2.0 seconds
35 and as slow as 28 seconds. The shut-down procedure
simply consisted of turning off the fuel supply and

letting the fuel dissipate by crossover of hydrogen and air through the electrolyte membranes.

The curve K represents controlled start-up and shut-down procedures, wherein the shut-down procedures were
5 according to the present invention. Upon start-up, with the anode flow field filled with air, hydrogen flow was commenced at a rate sufficient to produce a full anode flow field volume change in 0.40 seconds. The shut-down procedure, starting with the anode flow field filled with
10 hydrogen, displaced the hydrogen with air flowing at a rate sufficient to produce a full anode flow field volume change in 0.40 seconds.

The curve L represents controlled start-up and shut-down procedures like those used to produce curve K,
15 except nitrogen was used instead of hydrogen to purge the air from the anode flow field upon start-up, before introducing hydrogen into the anode flow field; and nitrogen was used to displace the hydrogen upon shut-down, prior to introducing any air into the anode flow
20 field. In both cases the nitrogen flow rate was sufficient to produce a full anode flow field volume change in 0.40 seconds. Curve L therefore represents the prior art nitrogen purging procedure discussed in the Background Information section of this specification.
25 Referring to Fig. 3, from curve J it can be seen that after approximately 250 "uncontrolled" cycles the average cell performance loss was about 0.195 volts. In comparison, as shown by curve K, using the shut-down procedure of the present invention along with an
30 analogous start-up procedure, after 300 cycles the average cell performance loss was only 0.055 volts. That's less than 30% of the "uncontrolled" 250 cycle voltage loss, but with 20% more cycles. On the other hand, the prior art nitrogen purge technique resulted in
35 only a 0.04 volts loss after about 1500 cycles.

By way of explanation, when nitrogen is used as the purge gas, there is generally a trace of oxygen in the nitrogen gas stream as a result of the nitrogen production process and/or as a result of oxygen crossover
5 from the cathode flow field through the PEM membrane. That accounts for the small performance decay, with time, even when nitrogen is used. If the purge flow rate of nitrogen were increased, these losses would be reduced. The same is true for losses incurred using the procedures
10 represented by curve K. Thus, if the purge flow rates represented by curve K are increased, the difference between curves K and L will decrease. It is estimated that curve K would closely approach or be insignificantly different from curve L if the curve K purge flow rates
15 were increased to produce a full anode flow field volume change in 0.05 seconds or less. In that case, the present invention would provide all the benefits of a nitrogen purge without the complexity, cost and additional equipment volume necessitated by the use of
20 nitrogen.

Although the invention has been described and illustrated with respect to the exemplary embodiments thereof, it should be understood by those skilled in the art that the foregoing and various other changes,
25 omissions and additions may be made without departing from the spirit and scope of the invention.